

ADXNP030 SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A



Product designation				Soft starter advanced
Product type designat	tion			ADXNP
Motor type				Asynchronous
				three phase
Electrical features				
Supplies voltage				
		Type of system	V	Three phase 208…600VAC
		Rated supply voltage	V	100240VAC
		auxiliary supply voltage (Us)		
Datad starter surrent l		Rated frequency	Hz A	50/60 30
Rated starter current I	le		A	30
Rated motor power	IEC ratings (T<10°C)			
	IEC ratings (T≤40°C)	230VAC	kW	7.5
		400VAC	kW	15
		400VAC 500VAC	KW	18.5
	UL ratings (T≤40°C)	500VAC	rvv	10.5
		220-240VAC	HP	10
		380-415VAC	HP	15
		440-480VAC	HP	20
		550-600VAC	HP	25
Number of controlled phases		550 000 VAO	Nr.	2
Built-in bypass	phases		111.	Yes
				Natural or forced
Cooling System				(optional)
Rated insulation voltage	ge Ui		V	600
Programming interfac	-			
				Settings: starting voltage, acceleration
Potentiometer				ramp, deceleration ramp. Note. Potentiometers can be disabled via NFC.
Display				No
Programming with NF	C technology			Yes
Optical port				Yes
Startup and stop settin	ngs			
Startup method				Voltage ramp witl current limit
Stop method				Voltage ramp or free-wheel stop
			-	

Acceleration ramp

Deceleration ramp

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding

1-20

0-20

s

s



ADXNP030 SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BYPASS RELAY.

ENERGY AND AUTOMATION

AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A

		%	30-80
Startup voltage Protections		70	
Power supply Protection			No power line, phase loss, frequency out of limits, minimum and maximum voltage and phase sequence
Motor protection			Electronic current thermal protection (overload), locked rotor, current asymmetry, load too low, starting too long
Starter protection			Overtemperature and overcurrent
Input and Output			
Digital inputs			
	Number of digital input Digital input type Digital input functions	Nr.	1 Volt-free contact Motor start
Digital outputs	Number of digital output	Nr.	2 2 NO contacts
	Digital output arrangement Digital output functions		with the same common, 5A 250VAC AC1 - 5A 30 VDC Programmable: line contactor (Run), TOR (Top Of Ramp), alarm,
Communication interfaces			max torque
Communication interface			NFC, optical port for the connection of USB (CX01) and Wi-Fi (CX02) devices, optional
			RS485 module (CX04) Modbus RTU protocol
	min	°C	-20 +60°C (with
	max	°C	current derating >40°C)
Storage temperature		°C	
Otorage temperature			
Communication interface Ambient conditions Temperature Operating temperature		°C °C	USB (CX01) an Wi-Fi (CX02) devices, optiona RS485 module (CX04) Modbus RTU protocol -20 +60°C (with current derating

ADXNP030


The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



ADXNP030 SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A

Max altitude	m	1000 without derating of the starter current
Relative humidity	%	<80%
Pollution degree		2
Installation category		
Housing		
Mounting		Screw-fixing or 35mm DIN rail (IEC/EN/BS 60715)
IP degree of protection		IP20
Dimensions (W x H x D)		45 x 159 x 128.4
Weight	Kg	0.66

Dimensions



Certifications and compliance

e er inteation e and e	empilance	
Compliance		
	CSA C22.2 n° 60947-4-2	
	IEC/EN/BS 60947-1	
	IEC/EN/BS 60947-4-2	
	UL 60947-4-2	
Certificates		
	cULus	
	EAC	
	RCM (pending)	
ETIM classification		
		EC000640 - Soft

ETIM 8.0

EC000640 - Soft starter

ADXNP030