

## ADXNP01824 SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A



Product designation				Soft starter advanced
Product type designation				ADXNP
Motor type				Asynchronous three phase
Electrical features				
Supplies voltage				
		Type of system		Three phase
		Rated supply voltage	V	208600VAC
		auxiliary supply voltage (Us)		24VAC/DC
		Rated frequency	Hz	50/60
Rated starter current le			Α	18
Rated motor power				
	IEC ratings (T≤40°C)			
		230VAC	kW	4
		400VAC	kW	7.5
		500VAC	KW	11
	UL ratings (T≤40°C)			
		220-240VAC	HP	5
		380-415VAC	HP	10
		440-480VAC	HP	10
		550-600VAC	HP	15
Number of controlled p	phases		Nr.	2
Built-in bypass				Yes
Cooling System				Natural or forced (optional)
Rated insulation voltage Ui			V	600
Programming interface	•			
				Settings: starting voltage, acceleration ramp,
Potentiometer				deceleration ramp. Note. Potentiometers can be disabled via NFC.
Display				No
Programming with NFC	C technology			Yes
Optical port				Yes
Startup and stop settin	as			
Startup method	<u> </u>			Voltage ramp with current limit
Stop method				Voltage ramp or free-wheel stop
Acceleration ramp			S	1-20
Deceleration ramp			S	0-20

ADXNP01824

The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



## **ADXNP01824** SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BY-PASS RELAY.

ENERGY AND AUTOMATION

AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Startup voltage		%	30-80
Protections			
Power supply Protection			No power line, phase loss, frequency out of limits, minimum and maximum voltage and phase sequence
Motor protection			Electronic current thermal protection (overload), locked rotor, current asymmetry, load too low, starting too long
Starter protection			Overtemperature and overcurrent
Input and Output			
Digital inputs			
	Number of digital input Digital input type Digital input functions	Nr.	1 Volt-free contact Motor start
Digital outputs	Number of digital output	Nr.	2 2 NO contacts with the same
	Digital output arrangement Digital output functions		common, 5A 250VAC AC1 - 5A 30 VDC Programmable: line contactor (Run), TOR (Top Of Ramp), alarm, max torque
Communication interfaces			
Communication interface			NFC, optical port for the connection of USB (CX01) and Wi-Fi (CX02) devices, optional RS485 module (CX04) Modbus RTU protocol
Ambient conditions			
Temperature Operating temperature			
	min	°C °C	-20 +60°C (with
	max	U	current derating >40°C)
Storage temperature	min	°C °C	-30 +80
	max	U	TOU

ADXNP01824


The characteristics described in this document are subject to updates or modifications at any time. The descriptions, technical and functional information, illustrations and instructions in this brochure are purely illustrative, and are consequently not contractually binding



## ADXNP01824 SOFT STARTER, ADXNP... TYPE, ADVANCED VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Max altitude	m	1000 without derating of the starter current
Relative humidity	%	<80%
Pollution degree		2
Installation category		
Housing		
Mounting		Screw-fixing or 35mm DIN rail (IEC/EN/BS 60715)
IP degree of protection		IP20
Dimensions (W x H x D)	mm	45 x 139 x 113.4
Weight	Kg	0.47

Dimensions



## Certifications and compliance

Compliance

Compliance		
	CSA C22.2 n° 60947-4-2	
	IEC/EN/BS 60947-1	
	IEC/EN/BS 60947-4-2	
	UL 60947-4-2	
Certificates		
	cULus	
	EAC	
	RCM (pending)	
ETIM classification		
		EC000640 - Soft

ETIM 8.0

EC000640 - Soft starter

ADXNP01824